



Inrico S100 4G PoC Radio

Terminal Default Buttons using iConvNet PTT App



version 8.1

Guide

- Short press
- Long press



Tested Accessories



SPM-M3
Inrico Value Speaker Microphone



RSM-300-M3
Wirox Inrico Universal Speaker Microphone



BP01
Bluetooth PTT Button



B01
Inrico Bluetooth Microphone

iConvNet™

1 Please note: Inrico PoC radios offer programmable buttons, allowing customization for different functions and requirements through the iConvNet PTT App. Keep in mind that the button configurations may vary when using alternative apps.

Connection

Canada and US Version	GSM: B2, B3, B5, B8 WCDMA: B2, B4, B5 TDD-LTE: B38, B40 FDD-LTE: B2, B3, B4, B5, B7, B8, B12, B17, B28A, B28B, B66
Wi-Fi	802.11 a/b/g/n 2.4G/5G
Bluetooth	BT4.2 (low power)
Navigation	GPS
NFC	Support

Hardware

CPU	MTK6739V/WA
RAM + ROM	1GB + 8GB
Expand Memory	Optional, up to 32G
Card Slot	Micro SIM Card+TF Card
USB Port	Micro USB
Interface	M3
Screen Size	2.8 Inch Touch Screen (240*320)
Camera	Front Camera 2.0MP, Rear Camera 13.0MP
Speaker	Ø36mm, 8Ω 2W
Microphone	Main MIC + Dual Auxiliary MIC
Battery	4000mAh
Working Times	21 Hours (5/5/90 standard test)
Standby Times	25 Hours
Dimension (H*W*D)	129.2 x 67 x 26mm
Weight	≈220g
Working Temp.	-10°C ~ 60°C
Storage Temp.	-20°C ~ 70°C
Flashlight	Support

Certification

Ingress Protection	IP65
Drop Certification	1.2 Meter CE/FCC/ROHS/CMIT ID:2019CP4502/CTA/3C